

Bill of materials
Table 1. STEVAL-VL53L9 bill of materials

Item	Q.ty	Ref.	Part/value	Description	Manufacturer	Order code
1	3	R23, R24, R25	0R	RES, 0R, Jumper, 1/16W, 0402	Yageo	RC0402JR-070RL
2	4	C9, C12, C15, C16	1uF	CAP, CER, 1uF, 35V, X5R, 0402	Murata	GRM155R6YA105KE11D
3	2	R7, R8	2.2k	RES, 2.2k, 1%, 1/16W, 0402	Yageo	RC0402FR-072K2L
4	1	J2	2.54mm, T/H, Vert	CONN, HEADER, 08 POS, 8x1, 2.54mm, T/H, VERT	Harwin	M20-9990845
5	1	J3	3x1, 1.27mm, T/H, Male	CONN, HEADER, 3POS, 1.27MM, T/H, MALE	Harwin	M50-3530342
6	2	C8, C10	4.7uF	CAP, CER, 4.7uF, 6.3V, X5R, 0402	TDK	C1005X5R0J475K050BC
7	3	C14, C19, C20	10nF	CAP, CER, 10nF, 25V, X5R, 0402	AVX	04023D103KAT2A
8	5	C6, C7, C13, C17, C18	10uF	CAP, CER, 10uF, 6.3V, X5R, 0402	Murata	GRJ155R60J106ME11D
9	1	Y1	12MHz 50ppm	XTAL OSC XO 12MHZ CMOS SMD	ECS Inc.	ECS-2520MVLG-120-CN-TR
10	1	J1	22 way, 0.5 mm Pitch	Connecteurs FFC et FPC 0.5MM 22 POS bottom contact	Hirose	FH12-22S-0.5SH(55)
11	5	R2, R4, R6, R9, R20	47k	RES, 47k, 1%, 1/10W, 0402	Panasonic	ERJ2RKF4702X
12	7	C1, C2, C3, C4, C5, C11, C21	100nF	CAP, CER, 100nF, 10%, 50V, X7R, 0402	Murata	GRT155R71H104KE01D
13	1	JP3[1-2]	Black	JUMPER, 1.27MM, BLACK	Harwin	M50-1900005
14	1	U7	LDK130M12R, SOT23-5	IC, REG, LDO, 1.2V, 0.3A, SOT23-5	ST	LDK130M12R
15	1	U6	LDK130M18R, SOT23-5	IC, REG, LDO, 1.8V, 0.3A, SOT23-5	ST	LDK130M18R
16	1	U5	LDK130M28R, SOT23-5	IC, REG, LDO, 2.8V, 0.3A, SOT23-5	ST	LDK130M28R
17	1	U4	M24C64-DFCT6TP/K, WLCSP	IC EEPROM 64KBIT I2C 1MHZ 8WLCSP	ST	M24C64-DFCT6TP/K
18	2	U1, U2	PI4ULS3V204	IC, 4-Bit Bi-directional Level Shifter, TQFN3.5x3.5-14	Diodes Incorporated	PI4ULS3V204ZBEX
19	1	U3	VL53L9CXV0VE/1, OPTICAL LGA 12.1X5.1X4.5MM	VL53L9 ToF Module	ST	VL53L9CXV0VE/1
20	0	R17, R18	2.2k	RES, 2.2k, 1%, 1/16W, 0402	Yageo	RC0402FR-072K2L
21	0	R1, R3, R5, R10	47k	RES, 47k, 1%, 1/10W, 0402	Panasonic	ERJ2RKF4702X
22	0	JP3[2-3]	Black	JUMPER, 1.27MM, BLACK	Harwin	M50-1900005

IMPORTANT NOTICE – READ CAREFULLY

STMicroelectronics NV and its subsidiaries (“ST”) reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice.

In the event of any conflict between the provisions of this document and the provisions of any contractual arrangement in force between the purchasers and ST, the provisions of such contractual arrangement shall prevail.

The purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST’s terms and conditions of sale in place at the time of order acknowledgment.

The purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of the purchasers’ products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

If the purchasers identify an ST product that meets their functional and performance requirements but that is not designated for the purchasers’ market segment, the purchasers shall contact ST for more information.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, refer to www.st.com/trademarks. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2026 STMicroelectronics – All rights reserved